



Publication number: **0 641 108 A2**

EUROPEAN PATENT APPLICATION

Application number: **94305853.7**

Int. Cl.⁶: **H04L 12/56, H04Q 11/04, H04Q 3/52**

Date of filing: **05.08.94**

Priority: **27.08.93 GB 9317897**

Date of publication of application: **01.03.95 Bulletin 95/09**

Designated Contracting States: **DE ES FR IT SE**


Applicant: **GPT LIMITED**
New Century Park
P.O. Box 53
Coventry, CV3 1HJ (GB)

Inventor: **Burton, Nigel John**
22 Scutts Close
Lytchett Matravers, Poole BH16 (GB)

Representative: **Branfield, Henry Anthony**
The General Electric Company, p.l.c.
GEC Patent Department
Waterhouse Lane
Chelmsford, Essex CM1 2QX (GB)

Telecommunications switching element.

A multi-stage telecommunications switching means, such as a "rotator", has 2^n input ports and 2^n output ports, 'n' being an integer greater than 1, and is formed from a number $n \times y^{(n-1)}$ of $y \times y$ switching elements where 'y' is an integer greater than 1 and the elements are arranged in n stages wherein each switching element within a stage x, where 'x' is an integer between 1 and n, changes state every $y^{(x-1)}$ timeslots to provide switching only in the space domain. The switching elements may be electrical or optical devices.



EP 0 641 108 A2

The present invention relates to a telecommunications switching element referred to as a "rotator" and described in patent applications nos. GB2258360, GB2258366, GB2258581 and GB2258582 imported herein by reference.

According to the present invention there is provided a multi-stage telecommunications switching means having 2^n input and 2^n output ports, where 'n' is an integer greater than 1, comprising a number $n \times y^{(n-1)}$ of $x \times y$ switching elements where 'y' is an integer greater than 1 arranged in n stages wherein each switching element within a stage x, where x is an integer between 1 and n, changes state every $y^{(x-1)}$ timeslots to provide switching only in the space domain.

Further there is provided a multi-stage telecommunications switching means as above, having 2^n inputs and 2^n outputs, and wherein y is equal to 2, whereby there are $n \times 2^{(n-1)}$ switching elements arranged in 'n' stages and each switching element within a stage 'x', where x is an integer between 1 and n inclusive, changes state every $2^{(x-1)}$ timeslots.

The present invention will now be described, by way of example, with reference to the accompanying drawings, in which:-

- Figure 1 shows a rotator input channel map;
- Figure 2 shows a rotator output channel map;
- Figure 3(a) shows a basic 2×2 switching device;
- Figure 3(b) shows the device of Figure 4(a) in the "cross" state;
- Figure 3(c) shows the device of Figure 4(b) in the "bar" state;
- Figure 4 shows an interconnected array of devices of Figure 3(a); and
- Figure 5 shows two 4×4 rotators interconnected to provide an inverse transformation;

A Rotator is part of an ATM or STM switch fabric and performs a mixing and spatial routing function between its inputs and outputs. The Rotator described as an example has 16 inputs and 16 outputs. The inputs to the Rotator each have 16 slots in a conceptual frame. The Rotator space switches the slots so that each input has a single slot to each output per frame, and consequently each output has one slot from each input.

It is important that the Rotator preferably should introduce no additional delay, and therefore no timeswitching functions are possible. The present invention provides a Rotator function that satisfies the zero-delay requirement.

The invention further allows a migration from electrical to optical technology with no change to the control or timing relationship.

The rotator functionality can be represented by the input and output channel maps shown in Figures 1 and 2 respectively.

The input channel map in Figure 1 shows the 16 inputs to the rotator in the vertical dimension annotated by the numbers 1 to 16, and the 16 timeslots per cycle in the horizontal direction annotated A to P.

One internal cycle from input number 5 is highlighted for explanation. It can be seen that input number 5 is divided into 16 timeslots, A5 to P5. The rotator will take the 16 timeslots and transmit one to each central stage.

In the output channel map, Figure 2, one cycle to central stage switch 7 is highlighted, and it can be seen that sample C from input number 5 will be transmitted to central switch 7.

Note that all samples remain in their respective columns, i.e. they are not moved in the horizontal plane, which represents the time domain, but only moved in the vertical plane which represents the space domain. Thus no time switching is performed and therefore no additional delay is incurred in the rotator.

The Rotator, as shown in Figure 4, is implemented by means of multiple interconnected 2×2 switching elements (32 in total), Figure 3(a), which may be in turn be implemented either optically or electrically. The 2×2 element has two states, a 'cross' state and a 'bar' state, shown in Figures 3(b) and 3(c) respectively. A simple control interface switches the element between the 2 states. The 32 elements must be interconnected in the manner shown in Figure 4.

The timing of the control signals 'cross' and 'bar' with reference to the start of the frame is as shown below, where 'B' represents a 'bar' and 'C' a 'cross' signal.

Stage 1:																
All elements																
T/S:	1	2	3	4	5	6	7	8	9	10	11	12	13	14	15	16
State:	B	C	B	C	B	C	B	C	B	C	B	C	B	C	B	C

<u>Stage 2:</u>																
Elements 1, 3, 5, 7																
T/S:	1	2	3	4	5	6	7	8	9	10	11	12	13	14	15	16
State:	B	C	C	B	B	C	C	B	B	C	C	B	B	C	C	B
Elements 2, 4, 6, 8																
T/S:	1	2	3	4	5	6	7	8	9	10	11	12	13	14	15	16
State:	B	B	C	C	B	B	C	C	B	B	C	C	B	B	C	C

Stage 3:

Elements 1, 5

T/S: 1 2 3 4 5 6 7 8 9 10 11 12 13 14 15 16
 State: B C C C C B B B B C C C C B B B

Elements 2, 6

T/S: 1 2 3 4 5 6 7 8 9 10 11 12 13 14 15 16
 State: B B C C C C B B B B C C C C B B

Elements 3, 7

T/S: 1 2 3 4 5 6 7 8 9 10 11 12 13 14 15 16
 State: B B B C C C C B B B B C C C C B

Elements 4, 8

T/S: 1 2 3 4 5 6 7 8 9 10 11 12 13 14 15 16
 State: B B B B C C C C B B B B C C C C

Stage 4:

Element 1

5

T/S: 1 2 3 4 5 6 7 8 9 10 11 12 13 14 15 16

State: B C C C C C C C C B B B B B B B

10

Element 2

T/S: 1 2 3 4 5 6 7 8 9 10 11 12 13 14 15 16

State: B B C C C C C C C B B B B B B

15

Element 3

T/S: 1 2 3 4 5 6 7 8 9 10 11 12 13 14 15 16

State: B B B C C C C C C C C B B B B B

20

Element 4

T/S: 1 2 3 4 5 6 7 8 9 10 11 12 13 14 15 16

State: B B B B C C C C C C C C B B B B

25

Element 5

T/S: 1 2 3 4 5 6 7 8 9 10 11 12 13 14 15 16

State: B B B B B C C C C C C C C B B B

30

35

40

Element 6

T/S: 1 2 3 4 5 6 7 8 9 10 11 12 13 14 15 16

45

50

55

State: B B B B B B C C C C C C C C B B

Element 7

T/S: 1 2 3 4 5 6 7 8 9 10 11 12 13 14 15 16

State: B B B B B B B C C C C C C C C B

Element 8

T/S: 1 2 3 4 5 6 7 8 9 10 11 12 13 14 15 16

State: B B B B B B B B C C C C C C C C

The implementation described performs the required functionality of the Rotator with zero delay (except for propagation delay), and can either be implemented using electronic or optic technology using the same control and timing information. Both Lithium Niobate and Indium Phosphide are suitable materials for optic implementation of the Rotator function.

Using a pair of interconnected Rotators R1, R2, shown in Figure 5 as 4 x 4 units for this example, such that $R2 = [R1]^{-1}$, i.e. R2 performs the inverse function to R1 leaving the inputs unchanged for each Rotator.

Ad, Bd, Cd, Dd represent the data from inputs A, B, C, D respectively and Ah, Bh, Ch, Dh represent the header information from inputs A, B, C, D respectively.

The header information is switched by R1 to the Header Processing where SOH handling, ATM cell header translation/policing and other functions can be carried out to provide modified headers Ah', Bh', Ch', Dh'. Equivalent delays are then applied to the data by the Delay Unit. The data streams are then reconstituted by the Rotator R2.

Claims

1. A multi-stage telecommunications switching means having 2^n input and 2^n output ports, where 'n' is an integer greater than 1, comprising a number $n \times y^{(n-1)}$ of $y \times y$ switching elements, where 'y' is an integer greater than 1, arranged in n stages wherein each switching element within a stage x, where x is an integer between 1 and n, changes state every $y^{(x-1)}$ timeslots to provide switching only in the space domain.
2. A switching means as claimed in Claim 1, having 2^n inputs and 2^n outputs, wherein y is equal to 2, whereby there are $n \times 2^{(n-1)}$ switching elements arranged in 'n' stages and each switching element within a stage 'x', where x is an integer between 1 and n inclusive, changes state every $2^{(x-1)}$ timeslots.
3. A switching means as claimed in Claim 1 or 2 wherein each switching element has two states, a first state wherein each input port is connected to a corresponding output port and a second state wherein each input port is cross-connected to an opposite output port.
4. A switching means as claimed in any preceding claim wherein the switching elements are optical devices.
5. A processing means comprising first and second switching means as claimed in any preceding claim, wherein the second switching means performs a function inverse to that performed by the first switching means, further comprising a header processing unit connected between an output of the first switching means and the corresponding input of the second switching means.
6. A processing means as claimed in Claim 5, further comprising delay means between the remaining corresponding outputs of the first switching means and inputs of the second switching means.

A1	B1	C1	D1	E1	F1	G1	H1	I1	J1	K1	L1	M1	N1	O1	P1
A2	B2	C2	D2	E2	F2	G2	H2	I2	J2	K2	L2	M2	N2	O2	P2
A3	B3	C3	D3	E3	F3	G3	H3	I3	J3	K3	L3	M3	N3	O3	P3
A4	B4	C4	D4	E4	F4	G4	H4	I4	J4	K4	L4	M4	N4	O4	P4

A5	B5	C5	D5	E5	F5	G5	H5	I5	J5	K5	L5	M5	N5	O5	P5 --> From 5

A6	B6	C6	D6	E6	F6	G6	H6	I6	J6	K6	L6	M6	N6	O6	P6
A7	B7	C7	D7	E7	F7	G7	H7	I7	J7	K7	L7	M7	N7	O7	P7
A8	B8	C8	D8	E8	F8	G8	H8	I8	J8	K8	L8	M8	N8	O8	P8
A9	B9	C9	D9	E9	F9	G9	H9	I9	J9	K9	L9	M9	N9	O9	P9
A10	B10	C10	D10	E10	F10	G10	H10	I10	J10	K10	L10	M10	N10	O10	P10
A11	B11	C11	D11	E11	F11	G11	H11	I11	J11	K11	L11	M11	N11	O11	P11
A12	B12	C12	D12	E12	F12	G12	H12	I12	J12	K12	L12	M12	N12	O12	P12
A13	B13	C13	D13	E13	F13	G13	H13	I13	J13	K13	L13	M13	N13	O13	P13
A14	B14	C14	D14	E14	F14	G14	H14	I14	J14	K14	L14	M14	N14	O14	P14
A15	B15	C15	D15	E15	F15	G15	H15	I15	J15	K15	L15	M15	N15	O15	P15
A16	B16	C16	D16	E16	F16	G16	H16	I16	J16	K16	L16	M16	N16	O16	P16

Figure 1

A1	B16	C15	D14	E13	F12	G11	H10	I9	J8	K7	L6	M5	N4	O3	P2
A2	B1	C16	D15	E14	F13	G12	H11	I10	J9	K8	L7	M6	N5	O4	P3
A3	B2	C1	D16	E15	F14	G13	H12	I11	J10	K9	L8	M7	N6	O5	P4
A4	B3	C2	D1	E16	F15	G14	H13	I12	J11	K10	L9	M8	N7	O6	P5
A5	B4	C3	D2	E1	F16	G15	H14	I13	J12	K11	L10	M9	N8	O7	P6
A6	B5	C4	D3	E2	F1	G16	H15	I14	J13	K12	L11	M10	N9	O8	P7

A7	B6	C5	D4	E3	F2	G1	H16	I15	J14	K13	L12	M11	N10	O9	P8 --> To 7

A8	B7	C6	D5	E4	F3	G2	H1	I16	J15	K14	L13	M12	N11	O10	P9
A9	B8	C7	D6	E5	F4	G3	H2	I1	J16	K15	L14	M13	N12	O11	P10
A10	B9	C8	D7	E6	F5	G4	H3	I2	J1	K16	L15	M14	N13	O12	P11
A11	B10	C9	D8	E7	F6	G5	H4	I3	J2	K1	L16	M15	N14	O13	P12
A12	B11	C10	D9	E8	F7	G6	H5	I4	J3	K2	L1	M16	N15	O14	P13
A13	B12	C11	D10	E9	F8	G7	H6	I5	J4	K3	L2	M1	N16	O15	P14
A14	B13	C12	D11	E10	F9	G8	H7	I6	J5	K4	L3	M2	N1	O16	P15
A15	B14	C13	D12	E11	F10	G9	H8	I7	J6	K5	L4	M3	N2	O1	P16
A16	B15	C14	D13	E12	F11	G10	H9	I8	J7	K6	L5	M4	N3	O2	P1

Figure 2




Figure 3a




Figure 3b




Figure 3c




Figure 4




Figure 5

This Page Blank (uspto)

(19)



Europäisches Patentamt
European Patent Office
Office européen des brevets



(11)

EP 0 641 108 A3

(12)

EUROPEAN PATENT APPLICATION

(88) Date of publication A3:
18.11.1998 Bulletin 1998/47

(51) Int Cl.⁶: **H04L 12/56**, H04Q 11/04,
H04Q 3/52

(43) Date of publication A2:
01.03.1995 Bulletin 1995/09

(21) Application number: **94305853.7**

(22) Date of filing: **05.08.1994**

(84) Designated Contracting States:
DE ES FR IT SE

(72) Inventor: **Burton, Nigel John**
Lytchett Matravers, Poole BH16 (GB)

(30) Priority: **27.08.1993 GB 9317897**

(74) Representative: **Branfield, Henry Anthony**
The General Electric Company, p.l.c.
GEC Patent Department
Waterhouse Lane
Chelmsford, Essex CM1 2QX (GB)

(71) Applicant: **GPT LIMITED**
Coventry, CV3 1HJ (GB)

(54) Telecommunications switching element

(57) A multi-stage telecommunications switching means, such as a "rotator", has 2^n input ports and 2^n output ports, 'n' being an integer greater than 1, and is formed from a number $n \times y^{(n-1)}$ of $y \times y$ switching elements where 'y' is an integer greater than 1 and the el-

ements are arranged in n stages wherein each switching element within a stage x, where 'x' is an integer between 1 and n, changes state every $y^{(x-1)}$ timeslots to provide switching only in the space domain. The switching elements may be electrical or optical devices.




Figure 4



European Patent
Office

EUROPEAN SEARCH REPORT

Application Number
EP 94 30 5853

DOCUMENTS CONSIDERED TO BE RELEVANT			
Category	Citation of document with indication, where appropriate, of relevant passages	Relevant to claim	CLASSIFICATION OF THE APPLICATION (Int.Cl.6)
A	TARNG C -L ET AL: "FAIRNESS AND PRIORITY IMPLEMENTATION IN NON-BLOCKING COPY NETWORK" COMMUNICATIONS - RISING TO THE HEIGHTS, DENVER, JUNE 23 - 26, 1991, vol. 2, 23 June 1991, pages 1002-1006, XP000269635 INSTITUTE OF ELECTRICAL AND ELECTRONICS ENGINEERS * page 1002, left-hand column, line 45 - right-hand column, line 2 * * page 1002, right-hand column, line 42-43 * * page 1003, left-hand column, line 22-46 *	1-5	H04L12/56 H04Q11/04 H04Q3/52
A	LEE T H ET AL: "BANYAN NETWORK NONBLOCKING WITH RESPECT TO CYCLIC SHIFTS" ELECTRONICS LETTERS, vol. 27, no. 16, 1 August 1991, pages 1474-1476, XP000259878 * the whole document *	1,5	TECHNICAL FIELDS SEARCHED (Int.Cl.6)
D.A	GB 2 258 582 A (PLESSEY TELECOMM) 10 February 1993 * abstract *	1,5	H04L
A	CHIN-TAU LEA: "A NEW BROADCAST SWITCHING NETWORK" IEEE TRANSACTIONS ON COMMUNICATIONS, vol. 36, no. 10, 1 October 1988, pages 1128-1137, XP000111136 * figure 10 *	4	
The present search report has been drawn up for all claims			
Place of search THE HAGUE		Date of completion of the search 24 September 1998	Examiner Dhondt, E
<p>CATEGORY OF CITED DOCUMENTS</p> <p>X : particularly relevant if taken alone Y : particularly relevant if combined with another document of the same category A : technological background O : non-written disclosure F : intermediate document</p> <p>T : theory or principle underlying the invention E : earlier patent document, but published on, or after the filing date D : document cited in the application L : document cited for other reasons S : member of the same patent family, corresponding document</p>			

EPO FORM 1503 03 02 (P4/C01)